

Single output DC power supplies (with safety terminals Ø4mm)



GPS3030A



GPS3030D



GPS3030DD



GPR3510HD



GPR30H10A

REF.	GPS3030A	GPS3030D	GPS1850D	GPS3030DD	GPR3060D	GPR3510HD	GPR6030D	GPR30H10A	DC6140
Display type	TYPE A	TYPE D		TYPE DD				TYPE A	TYPE DD
Power	90VA			180VA à 1000VA					
Voltage	0 to 30V	0 to 30V	0 to 18V	0 to 30V	0 to 30V	0 to 35V	0 to 60V	0 to 300V	0 to 30V
Adjustable	by 2 knobs coarse and fine from 0 to Vmax								
Current	0 to 3A	0 to 3A	0 to 5A	0 to 3A	0 to 6A	0 to 10A	0 to 3A	0 to 1A	0 to 5A
Adjustable	by 2 knobs coarse and fine from 0 to I max or 0 to 0								1 setting
Regulation	Output voltage variation : < 0,01% + 3mV - Output current variation < 0,2% + 3mA by mains variation of 15% or load variation 0 ~ 100%								
Ripple & noise	0.5mVrms								
Protection	Electronic by current limitation against overload and short circuit								
Power source	Mains 120-240V - 50/60Hz								
Supplied with	Power lead and user's manual								

DISPLAY TYPE


A : analogue type (with voltmeter & ammeter) Class 2,5%

D : digital type. (1 switchable display for Voltage/current)

DD : 2 digital type (1 display for voltage + 1 display for current)

ADDITIONAL ACCESSORIES

Safety leads



OPTION

GREEN/YELLOW male earthing socket

Put a «-M» at the end of the references